



AiV-DN6002

| | |
|----------------------------------|----------------------------------------------------------|
| Model | AiV-DN6002 |
| Video input / output | 6 channel input + 2 channel PoE switch, 1 channel output |
| HDD support | - |
| SD card support | 2 x 128 Gb |
| Playback | 6 channels, D1 / 960H |
| Recording Channels | 4 channel D1 / 960H + 2 channel 720P, real time |
| Audio input/output | 6 channel input and 1 channel output (can be turned off) |
| Sensor input / output | 4 channel input / 1 channel output |
| G-sensor | Yes |
| VGA | Yes |
| LAN | RJ45 |
| Rs232 | 1 |
| Rs485 | 1 |
| Voice talkback port | Yes |
| Movement detection | Yes |
| Searchchannel mode | Time, date |
| System | Embedded Linux system, double MCU control |
| Time-lapse | Turn off function, time set between 5-7200 sec |
| Compression | H.264, main profile |
| Power | DC8-36V, anti-pulse voltage, low voltage protection |
| Operating temperature / humidity | From -65 to +65°C / ≤80% |